



Blackfin Processor Family

Cryptography
Rights Management
Open Source
Car Telematics
IPTV
Mobile TV
Driver Assistance
Biometrics
Streaming Media
High Definition



► Embedded Processing

Effects Processing
Triple Play
Audio Processing
VoIP
Embedded Security
GSM/EDGE
Baseband Processing
Digital Radio
Global Positioning
Packet Processing
GCC/Linux



Why Choose a Blackfin® Processor?

- High performance, 16-/32-bit processor core with DSP and RISC functionality and programmability
 - Eliminates need for multiple separate processors
- Large portfolio of products ranging from 300 MHz to 750 MHz
 - Best-in-class MHz/mW performance
- Software controlled dynamic power management
 - Extends battery life in portable applications
- Application-tuned system peripherals
 - Provides glueless connectivity to a variety of external devices
- Many low cost pin- and code-compatible models
- Industrial temperature range allows for wide range of applications
- Supported by easy to use, world-class development tools
- On-chip flash memory available on certain models
- Processors available with Lockbox™ Secure Technology
- World-class ecosystem components and RTOS offerings from leading partners
- On-chip low power codec available on certain models

Blackfin Processors

Part Number	Package ¹	Speed (MHz)	RAM Memory (kB)	Ambient Temp Range (°C)	Key Peripherals	Price Range @ 1k (\$U.S.) ²
ADSP-BF512BSWZ-3	176-lead LQFP	300	116	−40 to +85	PPI, SPI, SPORTs, TWI, UART	Contact ADI
ADSP-BF512BSWZ-4	176-lead LQFP	400		−40 to +85		
ADSP-BF512KBCZ-3	168-ball CSP_BGA	300		0 to 70		
ADSP-BF512KBCZ-4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF512KSWZ-3	176-lead LQFP	300		0 to 70		
ADSP-BF512KSWZ-4	176-lead LQFP	400		0 to 70		
ADSP-BF512BSWZ-3F4	176-lead LQFP	300		−40 to +85	PPI, SPI, SPORTs, TWI, UART, SPI flash	
ADSP-BF512BSWZ-4F4	176-lead LQFP	400		−40 to +85		
ADSP-BF512KBCZ-3F4	168-ball CSP_BGA	300		0 to 70		
ADSP-BF512KBCZ-4F4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF512KSWZ-3F4	176-lead LQFP	300		0 to 70		
ADSP-BF512KSWZ-4F4	176-lead LQFP	400		0 to 70		
ADSP-BF514BSWZ-3	176-lead LQFP	300	116	−40 to +85	PPI, SPI, SPORTs, TWI, UART, SDIO, CE-ATA, eMMC	
ADSP-BF514BSWZ-4	176-lead LQFP	400		−40 to +85		
ADSP-BF514KBCZ-3	168-ball CSP_BGA	300		0 to 70		
ADSP-BF514KBCZ-4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF514KSWZ-3	176-lead LQFP	300		0 to 70		
ADSP-BF514KSWZ-4	176-lead LQFP	400		0 to 70		
ADSP-BF514BSWZ-3F4	176-lead LQFP	300		−40 to +85	PPI, SPI, SPORTs, TWI, UART, SDIO, CE-ATA, eMMC, SPI flash	
ADSP-BF514BSWZ-4F4	176-lead LQFP	400		−40 to +85		
ADSP-BF514KBCZ-3F4	168-ball CSP_BGA	300		0 to 70		
ADSP-BF514KBCZ-4F4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF514KSWZ-3F4	176-lead LQFP	300		0 to 70		
ADSP-BF514KSWZ-4F4	176-lead LQFP	400		0 to 70		
ADSP-BF516BSWZ-3	176-lead LQFP	300	116	−40 to +85	PPI, SPI, SPORTs, TWI, UART, 10/100 Ethernet, SDIO, CE-ATA, eMMC	
ADSP-BF516BSWZ-4	176-lead LQFP	400		−40 to +85		
ADSP-BF516KBCZ-3	168-ball CSP_BGA	300		0 to 70		
ADSP-BF516KBCZ-4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF516KSWZ-3	176-lead LQFP	300		0 to 70		
ADSP-BF516KSWZ-4	176-lead LQFP	400		0 to 70		
ADSP-BF516BSWZ-3F4	176-lead LQFP	300		−40 to +85	PPI, SPI, SPORTs, TWI, UART, 10/100 Ethernet, SDIO, CE-ATA, eMMC, SPI flash	
ADSP-BF516BSWZ-4F4	176-lead LQFP	400		−40 to +85		
ADSP-BF516KBCZ-3F4	168-ball CSP_BGA	300		0 to 70		
ADSP-BF516KBCZ-4F4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF516KSWZ-3F4	176-lead LQFP	300		0 to 70		
ADSP-BF516KSWZ-4F4	176-lead LQFP	400		0 to 70		
ADSP-BF518BSWZ-3	176-lead LQFP	300	116	−40 to +85	PPI, SPI, SPORTs, TWI, UART, 10/100 Ethernet with 1588, SDIO, CE-ATA, eMMC	
ADSP-BF518BSWZ-4	176-lead LQFP	400		−40 to +85		
ADSP-BF518KBCZ-3	168-ball CSP_BGA	300		0 to 70		
ADSP-BF518KBCZ-4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF518KSWZ-3	176-lead LQFP	300		0 to 70		
ADSP-BF518KSWZ-4	176-lead LQFP	400		0 to 70		
ADSP-BF518BSWZ-3F4	176-lead LQFP	300		−40 to +85	PPI, SPI, SPORTs, TWI, UART, 10/100 Ethernet with 1588, SDIO, CE-ATA, eMMC, SPI flash	
ADSP-BF518BSWZ-4F4	176-lead LQFP	400		−40 to +85		
ADSP-BF518KBCZ-3F4	168-ball CSP_BGA	300		0 to 70		
ADSP-BF518KBCZ-4F4	168-ball CSP_BGA	400		0 to 70		
ADSP-BF518KSWZ-3F4	176-lead LQFP	300		0 to 70		
ADSP-BF518KSWZ-4F4	176-lead LQFP	400		0 to 70		

¹Packages: LQFP (low profile quad flat pack); CSP_BGA (chip scale package ball grid array); PBGA (plastic ball grid array).

²All pricing is budgetary and subject to change.

³Available in automotive grade.



Blackfin Processors (continued)

Part Number	Package ¹	Speed (MHz)	RAM Memory (kB)	Ambient Temp Range (°C)	Key Peripherals	Price Range @ 1k (\$U.S.) ²
ADSP-BF522KBCZ-3	289-ball CSP_BGA	300	132	0 to 70	PPI, SPI, SPORTs, NAND Interface, TWI, Host DMA, UART, Lockbox	Contact ADI
ADSP-BF522BBCZ-3A	208-ball CSP_BGA			−40 to +85		
ADSP-BF522KBCZ-3C2	289-ball CSP_BGA			0 to 70		
ADSP-BF522KBCZ-4	289-ball CSP_BGA	400		0 to 70		
ADSP-BF522BBCZ-4A ³	208-ball CSP_BGA			−40 to +85		
ADSP-BF522KBCZ-4C2	289-ball CSP_BGA			0 to 70		
ADSP-BF523KBCZ-5	289-ball CSP_BGA	533		0 to 70		
ADSP-BF523BBCZ-5A ³	208-ball CSP_BGA			−40 to +85		
ADSP-BF523KBCZ-5C2	289-ball CSP_BGA			0 to 70		
ADSP-BF523KBCZ-6	289-ball CSP_BGA	600				
ADSP-BF523KBCZ-6A	208-ball CSP_BGA					
ADSP-BF523KBCZ-6C2	289-ball CSP_BGA					
ADSP-BF524KBCZ-3	289-ball CSP_BGA		300	132	0 to 70	
ADSP-BF524BBCZ-3A	208-ball CSP_BGA	−40 to +85				
ADSP-BF524KBCZ-3C2	289-ball CSP_BGA	0 to 70				
ADSP-BF524KBCZ-4	289-ball CSP_BGA	400	0 to 70			
ADSP-BF524BBCZ-4A	208-ball CSP_BGA		−40 to +85			
ADSP-BF524KBCZ-4C2	289-ball CSP_BGA		0 to 70			
ADSP-BF525KBCZ-5	289-ball CSP_BGA	533	0 to 70			
ADSP-BF525BBCZ-5A ³	208-ball CSP_BGA		−40 to +85			
ADSP-BF525KBCZ-5C2	289-ball CSP_BGA		0 to 70			
ADSP-BF525KBCZ-6	289-ball CSP_BGA	600				
ADSP-BF525KBCZ-6A	208-ball CSP_BGA					
ADSP-BF525KBCZ-6C2	289-ball CSP_BGA					
ADSP-BF526KBCZ-3	289-ball CSP_BGA		300	132	0 to 70	
ADSP-BF526BBCZ-3A	208-ball CSP_BGA	−40 to +85				
ADSP-BF526KBCZ-3C2	289-ball CSP_BGA	0 to 70				
ADSP-BF526KBCZ-4	289-ball CSP_BGA	400	0 to 70			
ADSP-BF526BBCZ-4A	208-ball CSP_BGA		−40 to +85			
ADSP-BF526KBCZ-4C2	289-ball CSP_BGA		0 to 70			
ADSP-BF527KBCZ-5	289-ball CSP_BGA	533	0 to 70			
ADSP-BF527BBCZ-5A	208-ball CSP_BGA		−40 to +85			
ADSP-BF527KBCZ-5C2	289-ball CSP_BGA		0 to 70			
ADSP-BF527KBCZ-6	289-ball CSP_BGA	600	0 to 70			
ADSP-BF527KBCZ-6A	208-ball CSP_BGA		0 to 70			
ADSP-BF527KBCZ-6C2	289-ball CSP_BGA		0 to 70			

¹Packages: LQFP (low profile quad flat pack); CSP_BGA (chip scale package ball grid array); PBGA (plastic ball grid array).

²All pricing is budgetary and subject to change.

³Available in automotive grade.

Blackfin Processors (continued)

Part Number	Package ¹	Speed (MHz)	RAM Memory (kB)	Ambient Temp Range (°C)	Key Peripherals	Price Range @ 1k (\$U.S.) ²	
ADSP-BF531SBBC400	160-ball CSP_BGA	400	52	−40 to +85	PPI, UART, SPI, 2 SPORTs, 3 timers, 16 GPIOs	8.90 to 14.10	
ADSP-BF531SBBCZ400 ³	160-ball CSP_BGA						
ADSP-BF531SBSTZ400 ³	176-lead LQFP						
ADSP-BF531SBB400	169-ball PBGA						
ADSP-BF531SBBZ400 ³	169-ball PBGA						
ADSP-BF532SBBC400	160-ball CSP_BGA	400	84	−40 to +85			9.33 to 17.31
ADSP-BF532SBBCZ400 ³	160-ball CSP_BGA						
ADSP-BF532SBSTZ400 ³	176-lead LQFP						
ADSP-BF532SBB400	169-ball PBGA						
ADSP-BF532SBBZ400 ³	169-ball PBGA						
ADSP-BF533SBBC400	160-ball CSP_BGA	400	148	−40 to +85	PPI, UART, SPI, 2 SPORTs, 3 timers, 16 GPIOs	12.19 to 22.21	
ADSP-BF533SBBCZ400	160-ball CSP_BGA	400					
ADSP-BF533SBBZ400	169-ball PBGA	400					
ADSP-BF533SBSTZ400	176-lead LQFP	400					
ADSP-BF533SBBC500	160-ball CSP_BGA	500					
ADSP-BF533SBBCZ500 ³	160-ball CSP_BGA	500					
ADSP-BF533SBB500	160-ball CSP_BGA	500					
ADSP-BF533SBBZ500 ³	169-ball PBGA	500					
ADSP-BF533SBBC-5V	160-ball CSP_BGA	533					
ADSP-BF533SBBCZ-5V	160-ball CSP_BGA	533					
ADSP-BF533SKBC-6V	160-ball CSP_BGA	600		0 to 70			
ADSP-BF533SKBCZ-6V	160-ball CSP_BGA	600					
ADSP-BF533SKBC750	160-ball CSP_BGA	750					
ADSP-BF534BBC-4A	182-ball CSP_BGA	400	132	−40 to +85	CAN, PPI/SPI, TWI, 8 timers, 48 GPIOs, 2 SPORTs/UARTs	12.40 to 18.53	
ADSP-BF534BBCZ-4A ³	182-ball CSP_BGA	400					
ADSP-BF534BBCZ-4B ³	208-ball CSP_BGA	400					
ADSP-BF534BBC-5A	182-ball CSP_BGA	500					
ADSP-BF534BBCZ-5A	182-ball CSP_BGA	500					
ADSP-BF534BBCZ-5B ³	208-ball CSP_BGA	500					
ADSP-BF534YBCZ-4B	208-ball CSP_BGA	400		−40 to +85			
ADSP-BF535PBB-200	260-ball PBGA	200	308	−40 to +85	2 SPIs, 2 SPORTs, USB device, PCI	30.36 to 45.92	
ADSP-BF535PBBZ-200	260-ball PBGA	200		−40 to +85			
ADSP-BF535PKB-300	260-ball PBGA	300		0 to 70			
ADSP-BF535PKBZ-300	260-ball PBGA	300		0 to 70			
ADSP-BF535PBB-300	260-ball PBGA	300		−40 to +85			
ADSP-BF535PKB-350	260-ball PBGA	350		0 to 70			
ADSP-BF535PKBZ-350	260-ball PBGA	350		0 to 70			
ADSP-BF536BBC-3A	182-ball CSP_BGA	300	100	−40 to +85	10/100 Ethernet, CAN, PPI, TWI, 8 timers, 48 GPIOs, 2 SPORTs/UARTs, SPI	10.07 to 14.42	
ADSP-BF536BBCZ-3A	182-ball CSP_BGA	300					
ADSP-BF536BBCZ-3B	208-ball CSP_BGA	300					
ADSP-BF536BBC-4A	182-ball CSP_BGA	400					
ADSP-BF536BBCZ-4A	182-ball CSP_BGA	400					
ADSP-BF536BBCZ-4B	208-ball CSP_BGA	400					

¹Packages: LQFP (low profile quad flat pack); CSP_BGA (chip scale package ball grid array); PBGA (plastic ball grid array).

²All pricing is budgetary and subject to change.

³Available in automotive grade.



Blackfin Processors (continued)

Part Number	Package ¹	Speed (MHz)	RAM Memory (kB)		Ambient Temp Range (°C)	Key Peripherals	Price Range @ 1k (\$U.S.) ²			
ADSP-BF537BBC-5A	182-ball CSP_BGA	500	132		−40 to +85	10/100 Ethernet, CAN, PPI, TWI, 8 timers, 48 GPIOs, 2 SPORTs/UARTs, SPI	17.15 to 21.20			
ADSP-BF537BBCZ-5A	182-ball CSP_BGA	500								
ADSP-BF537BBCZ-5B	208-ball CSP_BGA	500								
ADSP-BF537BBCZ-5AV	182-ball CSP_BGA	533								
ADSP-BF537BBCZ-5BV	208-ball CSP_BGA	533								
ADSP-BF537KBCZ-6AV	182-ball CSP_BGA	600								
ADSP-BF537KBCZ-6BV	208-ball CSP_BGA	600								
ADSP-BF538BBCZ-4A	316-ball CSP_BGA	400	148		−40 to +85	CAN 2.0B, 54 GPIOs, 4 SPORTs, 3 UARTs, 3 SPIs, 2 TWIs, PPI, flash	16.03 to 20.67			
ADSP-BF538BBCZ-4F4	316-ball CSP_BGA	400	148	Flash Memory 512						
ADSP-BF538BBCZ-4F8	316-ball CSP_BGA	400	148	Flash Memory 1MB						
ADSP-BF538BBCZ-5A ³	316-ball CSP_BGA	533	148							
ADSP-BF538BBCZ-5F4 ³	316-ball CSP_BGA	533	148	Flash Memory 512						
ADSP-BF538BBCZ-5F8 ³	316-ball CSP_BGA	533	148	Flash Memory 1MB						
ADSP-BF539BBCZ-5A ³	316-ball CSP_BGA	533	148			MXVR, CAN, 54 GPIOs, 4 SPORTs, 3 UARTs, 3 SPIs, 2 TWIs, PPI, flash	Contact ADI			
ADSP-BF539BBCZ-5F4 ³	316-ball CSP_BGA	533	148	Flash Memory 512						
ADSP-BF539BBCZ-5F8 ³	316-ball CSP_BGA	533	148	Flash Memory 1MB						
ADSP-BF542BBCZ-4A	400-ball CSP_BGA	400	132		−40 to +85	CAN ⁴ HS USB OTG, 3 EPPIs, Pixel comp, ATAPI-6, Lockbox	15.66 to 20.71			
ADSP-BF542BBCZ-5A ³	400-ball CSP_BGA	533			−40 to +85					
ADSP-BF542KBCZ-6A	400-ball CSP_BGA	600			0 to 70					
ADSP-BF542MBBCZ-5M ⁵	400-ball CSP_BGA	533			−40 to +85					
ADSP-BF544BBCZ-4A	400-ball CSP_BGA	400	132		−40 to +85	CAN ⁴ Host DMA, 3 EPPIs, Pixel comp, Lockbox		15.66 to 20.71		
ADSP-BF544BBCZ-5A ³	400-ball CSP_BGA	533	196							
ADSP-BF544MBBCZ-5M ⁵	400-ball CSP_BGA	533	132							
ADSP-BF547BBCZ-5A	400-ball CSP_BGA	533	260		−40 to +85	HS USB OTC, 3 EPPIs, Pixel comp, ATAPI-6, Lockbox			15.66 to 20.71	
ADSP-BF547KBCZ-6A	400-ball CSP_BGA	600	260		0 to 70					
ADSP-BF547MBBCZ-5M ⁵	400-ball CSP_BGA	533	132		−40 to +85					
ADSP-BF548BBCZ-5A	400-ball CSP_BGA	533	260		−40 to +85	HS USB OTG, 3 EPPIs, Pixel comp, ATAPI-6, Lockbox, CAN				15.66 to 20.71
ADSP-BF548MBBCZ-5M ⁵	400-ball CSP_BGA	533	132							
ADBF549WBBCZ502 ^{3, 5}	400-ball CSP_BGA	533	260			MXVR, CAN, HS USB OTG, ATAPI-6, 3 EPPIs, Pixel comp, Lockbox				
ADBF549MWBBCZ503 ^{3, 5}	400-ball CSP_BGA	533	132							
ADSP-BF561SKBZ500	297-ball PBGA	500	328		0 to 70	2 PPIs, UART, 12 timers, 2 SPORTs	25.20 to 35.74			
ADSP-BF561SKBCZ-5A	256-ball CSP_BGA	500			0 to 70					
ADSP-BF561SKBCZ-5V	256-ball CSP_BGA	533			0 to 70					
ADSP-BF561SBB500	297-ball PBGA	500			−40 to +85					
ADSP-BF561SBBZ500 ³	297-ball PBGA	500			−40 to +85					
ADSP-BF561SBBBCZ-5A ³	256-ball CSP_BGA	500			−40 to +85					
ADSP-BF561SKBZ600	297-ball PBGA	600			0 to 70					
ADSP-BF561SKBCZ-6A	256-ball CSP_BGA	600			0 to 70					
ADSP-BF561SKBCZ-6V	256-ball CSP_BGA	600			0 to 70					
ADSP-BF561SBB600	297-ball PBGA	600			−40 to +85					
ADSP-BF561SBBZ600	297-ball PBGA	600			−40 to +85					

¹Packages: LQFP (low profile quad flat pack); CSP_BGA (chip scale package ball grid array); PBGA (plastic ball grid array).

²All pricing is budgetary and subject to change.

³Available in automotive grade.

⁴Available on automotive-grade parts only.

⁵M designates support for 1.8 V mobile DDR memory.

Development Tools

The Blackfin processor is supported by the Analog Devices CROSSCORE® line of robust and flexible development tools.

VisualDSP++® Software

VisualDSP++ software delivers efficient project management, enabling programmers to move easily between editing, building, and debugging within a single interface. Key features include an optimizing C/C++ compiler, advanced plotting tools, embedded OS support (VDK), award-winning statistical profiling, TCP/IP and USB support, free software upgrades, and technical support.

EZ-KIT Lite® Evaluation Kit

The EZ-KIT Lite evaluation kit is a standalone evaluation board and evaluation suite of VisualDSP++ software to facilitate architecture evaluation.

EZ-Extender® Daughter Boards

EZ-Extender daughter boards enable developers to access and connect various peripherals from Analog Devices and third parties to the expansion interface of the EZ-KIT Lite evaluation kits.

Emulators

The USB-based and high performance (HP) USB-based emulators are easy, portable, nonintrusive, target-based debugging solutions. The HP USB-based emulator also supports the background telemetry channel (BTC), a nonintrusive method for exchanging data between the host and the target application without affecting the target system's real-time extended support characteristics.

EZ-Board™ Evaluation Boards

The EZ-Board evaluation board provides developers with a low cost platform for initial evaluation of the processors via an external emulator or μ Clinix.™ The EZ-Board evaluation board has an expansion interface that allows for modularity with different EZ-Extender boards.

Debug Agent Board

The Standalone Debug Agent is intended to provide a modular low cost emulation solution for EZ-Board evaluation boards as well as evaluation boards designed by third parties. The Standalone Debug Agent is very similar to the Debug Agent that is on existing EZ-KIT Lite evaluation boards but will have the flexibility to move from one board to another board.

Software Modules

Analog Devices has a wide range of tested and optimized software modules available, including decoders, encoders, codecs, and other algorithms that provide multimedia functions for the Blackfin and SHARC processor families. The software modules allow engineers to quickly and easily incorporate these functions, providing a faster development path to the end product. In addition, the highly optimized software modules feature a consistent API and framework to ensure rapid development of multiple functions. Also available is VisualAudio® 2.6 software, which enables engineers from other backgrounds to leverage a set of basic audio libraries and tools to jump-start their projects, modularize the development process, and shorten the learning curve.

Platforms and Reference Designs

Platforms and reference designs help jump-start your design. They include comprehensive software suites with documented APIs running on application-specific evaluation boards. The easy to use APIs enable customization and control of core system functions, letting you focus on adding value through product differentiation. For more information on Analog Devices platforms, reference designs, and third-party reference designs, visit www.analog.com/software.

Extended Development Tools and Support

Starter Kits

Analog Devices Starter Kits provide everything you need to get started on an application. Kits contain a Blackfin EZ-KIT Lite, EZ-Extender daughter board(s), and the software development kit (SDK), which contains sample code, "how to" documents, and various encoders/decoders that make getting started on an application easy and shorten the learning curve.

Software Development Kits

The SDK contains example software, source code, device drivers, algorithms, utilities information, and application notes that allow you to develop processor applications. The software can be used as a framework, or as examples of how to use certain aspects and peripherals, in conjunction with an ADI processor. The SDK is included in the starter kits and is also downloadable for free, provided you have the required hardware, at www.analog.com/sdk/downloads.

μ Clinix

The μ Clinix kernel and GNU toolchain are available for the Blackfin processor and can be downloaded from the μ Clinix for Blackfin processor website (www.blackfin.uclinux.org), which is the central repository for all Blackfin processor open-source projects. One of the board support packages available is the ADSP-BF537 STAMP μ Clinix kernel board support package (BSP). The BSP is composed of the ADSP-BF537 STAMP development board (including the full complement of memory along with serial and network interfaces), a recent copy of the open-source development tools, μ Clinix kernel, and bootloader. The STAMP board is specifically designed to support the development and porting of open-source μ Clinix applications.

NI LabVIEW™ Embedded Module for ADI Blackfin Processors

The NI LabVIEW Embedded Module for ADI Blackfin processors is a comprehensive graphical development environment for embedded design. This module builds on NI LabVIEW embedded technology, which facilitates dataflow graphical programming for embedded systems and includes hundreds of analysis and signal processing functions, integrated I/O, and an interactive debugging interface. With the NI LabVIEW Embedded Module for ADI Blackfin processors, users can easily access essential VisualDSP++ specific compiler options through LabVIEW, such as the ability to enable cache, optimize linking, and view live front-panel updates via JTAG. To help debug those challenging designs, users can connect the host development PC evaluation hardware or end product using an ADI JTAG emulator. LabVIEW includes a wide array of built-in visualization features including tools for charting and graphing real-time data, and reconfiguring attributes of data presentation, such as colors, font size, and graph types. Furthermore, users can dynamically tune applications at run time through live front panel controls.



Blackfin Processor Development Tools

Blackfin Processor	Hardware	Emulator	VisualDSP++ Development Software	Additional Software Available
ADSP-BF512 ADSP-BF514 ADSP-BF516 ADSP-BF518	ADZS-BF518F-EZBRD Key Features - ADSP-BF518F Blackfin processor - SDRAM - Flash - SPI flash - Audio codec - Power analysis interface - Ethernet PHY - A/D converter - Thumbwheel - UART - RTC battery	ADZS-BF518F-EZLITE		
ADSP-BF522 ADSP-BF522C ADSP-BF524 ADSP-BF524C ADSP-BF526 ADSP-BF526C	ADZS-BF526-EZBRD Key Features - ADSP-BF526 Blackfin processor - SDRAM - Flash: 4 MB (2M × 16) - NAND flash: 2 Gb - SPI flash - Audio codec - Power analysis interface - Ethernet PHY	ADZS-BF526-EZLITE ADZS-DBGAGENT-BRD ADZS-BFLLCD-EZEXT		VDSP-LABVIEW-EMB (All parts except ADSP-BF535/ ADSP-BF561)
ADSP-BF523 ADSP-BF523C ADSP-BF525 ADSP-BF525C ADSP-BF527 ADSP-BF527C	ADZS-BF527-EZLITE Key Features - ADSP-BF527 Blackfin processor - SDRAM - NAND flash - Audio codec - HS USB OTG - LCD display - Touch screen/keyboard controller	ADZS-BF527-MPSKIT ADZS-BFAV-EZEXT ADZS-BFFPGA-EZEXT	ADZS-USB-ICE ADZS-HPUSB-ICE	VDSP-LABVIEW-EVAL (All parts except ADSP-BF535/ ADSP-BF561) VisualAudio (ADSP-BF527/ADSP-BF533 ADSP-BF537/ADSP-BF538/ ADSP-BF548/ADSP-BF561 only)
ADSP-BF531 ADSP-BF532 ADSP-BF533	ADZS-BF533-EZLITE Key Features - ADSP-BF533 Blackfin processor 64 MB (32M × 16-bit) SDRAM 2 MB (512k × 16-bit × 2) - Flash memory AD1836 96 kHz audio codec with 4 input and 6 output RCA jacks - ADV7183 video decoder with 3 input RCA jacks - ADV7171 video encoder with 3 output RCA jacks - ADM3202 RS-232 line driver/ receiver	ADZS-BF-EZEXT-1 ADZS-BFAV-EZEXT ADZS-USBLAN-EZEXT ADZS-BFAUDIO-EZEXT ADZS-BFFPGA-EZEXT ADZS-BF533-MMSKIT	VDSP-BKFN-PC-TEST VDSP-BLKFN-PC-FULL VDSP-BLKFN-PCFLOAT VDSP-BLKFN-PCFLT-5	Mathworks (ADSP-BF531/ADSP-BF532/ ADSP-BF533/ADSP-BF534/ ADSP-BF536/ADSP-BF537 only) µClinux—open source (Not available on the ADSP-BF535/ADSP-BF538/ ADSP-BF54x family) GNU toolchain (Not available for the ADSP-BF535/ ADSP-BF54x family)
ADSP-BF534 ADSP-BF536 ADSP-BF537	ADZS-BF537-EZLITE Key Features - ADSP-BF537 Blackfin processor - Max core clock rate of 600 MHz 64 MB (32M × 16) SDRAM, 4 MB (2M × 16) flash memory - SMSC LAN83C185 10/100 PHY with RJ45 connector - CAN TJA1041 transceiver with 2 RJ10 connectors - AD1871 96 kHz stereo ADC with 1/8" jack connector - AD1854 96 kHz stereo DAC with 1/8" jack connector - RS-232 UART line driver/receiver - National Instruments Educational Laboratory Virtual Instrumentation Suite (NI ELVIS) interface	ADZS-BFAV-EZEXT ADZS-BFLLCD-EZEXT ADZS-USBLAN-EZEXT ADZS-BFAUDIO-EZEXT ADZS-BFFPGA-EZEXT ADZS-BF537-ASKIT Additional Hardware - BF537-STAMP - PHYTEC Phycore®		

Blackfin Processor Development Tools (continued)

Blackfin Processor	Hardware		Emulator	VisualDSP++ Development Software	Additional Software Available
ADSP-BF538 ADSP-BF538F	ADZS-BF538F-EZLITE Key Features - ADSP-BF538F Blackfin processor 64 MB (32M × 16) SDRAM 4 MB (2M × 16) flash memory - ADM3202 RS-232 line driver/receiver - AD1871 96 kHz stereo ADC - AD1854 96 kHz stereo DAC - TJA1041 transceiver 2 RJ10 connectors 9 LEDs	ADZS-BFLLCD-EZEXT	ADZS-USB-ICE ADZS-HPUSB-ICE	VDSP-BKFN-PC-TEST VDSP-BLKFN-PC-FULL VDSP-BLKFN-PCFLOAT VDSP-BLKFN-PCFLT-5	VDSP-LABVIEW-EMB (All parts except ADSP-BF535/ ADSP-BF561)
ADSP-BF542 ADSP-BF544 ADSP-BF547 ADSP-BF548 ADSP-BF549	ADZS-BF548-EZLITE Key Features - ADSP-BF548 Blackfin processor - DDR SDRAM - BURST flash - NAND flash - Hard drive - LCD display - AC'97 codec - Ethernet PHY - Touch screen/keyboard controller	ADZS-BFAV-EZEXT ADZS-BFFPGA-EZEXT ADZS-BFLLCD-EZEXT ADZS-BF548-MPSKIT			VDSP-LABVIEW-EVAL (All parts except ADSP-BF535/ ADSP-BF561)
ADSP-BF561	ADZS-BF561-EZLITE Key Features - ADSP-BF561 Blackfin processor 64 MB (16M × 16-bit × 2) SDRAM 8 MB (4M × 16-bit) flash memory - AD1836 multichannel 96 kHz audio codec - RCA jacks for stereo audio input/output - ADV7183A advanced 10-bit video decoder 3 RCA jacks for composite (CVBS), differential component (YUV), or S-video (Y/C) input - ADV7179 chip scale NTSC/PAL video encoder 3 RCA jacks for composite (CVBS), component (RGB), differential component (YUV), or S-Video (Y/C) output				VisualAudio (ADSP-BF527/ADSP-BF533 ADSP-BF537/ADSP-BF538/ ADSP-BF548/ADSP-BF561 only)
					Mathworks (ADSP-BF531/ADSP-BF532/ ADSP-BF533/ADSP-BF534/ ADSP-BF536/ADSP-BF537 only)
					µClinux—open source (Not available on the ADSP-BF535/ADSP-BF538/ ADSP-BF54x family)
					GNU toolchain (Not available for the ADSP-BF535/ ADSP-BF54x family)

Blackfin Processor Product Portfolio

	Lower Power Highest Performance													
	Future	ADSP-BF512	ADSP-BF514 ADSP-BF516 ADSP-BF518	ADSP-BF522 ADSP-BF524 ADSP-BF526	ADSP-BF523 ADSP-BF525 ADSP-BF527	ADSP-BF531 ADSP-BF532	ADSP-BF533	ADSP-BF534 ADSP-BF536	ADSP-BF535	ADSP-BF537	ADSP-BF538 ADSP-BF539	ADSP-BF542 ADSP-BF544 ADSP-BF547 ADSP-BF548 ADSP-BF549	ADSP-BF561	Future
Low BOM Cost	•	•		•		•								
Baseline Connectivity	•	•		•	•	•	•						•	•
System-Level Connectivity			•	•	•			•	•	•	•	•		
Low Standby	•	•	•	•										
Lockbox™ Security		•	•	•	•							•		
System Integration (Flash, Mixed-Signal)	•	•	•	•	•						•			
600 MHz or Greater					•		•			•		•	•	•
Multicore													•	•

Blackfin Processor Target Applications

ADSP-BF512/ADSP-BF514/ADSP-BF516/ADSP-BF518: Low cost, low power general-purpose parts with enhanced Internet and consumer connectivity.

ADSP-BF523/ADSP-BF525/ADSP-BF527 and ADSP-BF522/ADSP-BF524/ADSP-BF526: Low power processors that balance the combination of high performance, power efficiency, and system integration to enable highly optimized designs.

ADSP-BF531/ADSP-BF532: Low power, general-purpose processors for audio, voice, imaging, biometrics, and industrial applications.

ADSP-BF533: High performance for consumer video, security/surveillance, broadband home gateways, and automotive vision systems.

ADSP-BF534: CAN® connectivity for automotive, industrial, and medical applications.

ADSP-BF535: Optimized for networked Internet appliances, central office/network switches, industrial control, and automation applications.

ADSP-BF536/ADSP-BF537: Embedded network connectivity for video, industrial, biometrics, instrumentation, medical, and consumer appliances.

ADSP-BF538/ADSP-BF538F: Ideally suited for a broad range of industrial, instrumentation, and medical appliance applications.

ADSP-BF542/ADSP-BF544/ADSP-BF547/ADSP-BF548/ADSP-BF549: High performance convergent multimedia processors with a flexible platform for industrial, instrumentation, consumer, communications, and automotive applications.

ADSP-BF561: Symmetric multiprocessor optimized for high performance signal and media processing.

Third-Party Developers

More than 130 third parties provide software, hardware, and consulting services to support Blackfin embedded processors. For more information, visit www.analog.com/processors/collaborative.

Hardware

- Companion chip/chipsets
- Development boards
- Development systems
- Emulators
- Evaluation/starter boards
- Reference designs
- COTS DSP boards
- Daughter cards
- Extender boards

Software and Algorithms

- Speech G.7xx
- Telephony (DTMF, caller ID, etc.)
- Echo cancellation
- Audio (MP3, AAC/AAC+, WMA9, Dolby®, DTS®, etc.)
- Video/imaging (JPEG, MPEG-2/MPEG-4, H.264, H.263, WMV9, etc.)
- Image processing
- Facial/object recognition software
- VoIP suites
- Embedded Web browser
- Voice recognition
- Proprietary algorithms (3D audio effects, etc.)

OS/RTOS

- Green Hills® Software/INTEGRITY®
- Green Hills Software/*ve/OSity*™
- Green Hills Software/*μ-ve/OSity*™
- Express Logic/ThreadX®
- Micriμm μC/OS-II
- Mentor Graphics®/Nucleus
- Quadros Systems/RTXC™ Quadros
- Unicoi Systems™/Fusion™
- KADAK Systems/KwikNet™
- Open Source/μ.Clinux
- ADI/VDK

Design Test Optimization

- National Instruments

Software IDDE Tools

- Green Hills Software/MULTI®
- GAIO TECHNOLOGY/Blackfin design kit

HW Development Kits

- PHYTEC/Rapid Development Kits

Complimentary Support Resources

Blackfin Visual Training and Development

www.analog.com/vld

Analog Devices Sales and Distributors

www.analog.com/salesdir

Processor and Development Tools

Technical Support

www.analog.com/processors/technicalsupport

North America and Asia

processor.support@analog.com

Europe

processor.europe@analog.com

ADI Processor Companion Power Selection Guide

How to Use Selection Guide

Determine peak current requirement for each processor power rail using **Spec** listed to the right. Then choose recommended regulators below that intersect with the • symbol. Using the required voltage for each pin of the processor, select a regulator that has the right V_{OUT} for that pin. The regulator input voltage needs to also be compatible with the source power rail.

									Blackfin Processor	
									Processor Type	16
									I_{PEAK} (A)	0.8
									Spec	EE-229, EE-297, EE-293
									I_{NOM} (A)	0.05
ADI Power Regulator										
Part Number	Regulator Type	V_{IN} Max (V)	V_{IN} Min (V)	V_{BIAS} Min (V)	I_{OUT} (A)	V_{OUT} Max (V)	V_{OUT} Min (V)	Operating Control		
ADP1621	SW controller boost	5.5	1.0	2.9	—	—	—	EN SK		
ADP1821	SW controller	5.5	3.7	3	20.0	—	0.6	EN		
ADP1823	2× SW controller	20.0	3.7	3.4	20.0	—	1.6	EN SS TK		
ADP1828	SW controller	24.0	1.0	3	20.0	—	0.6	EN SS TK PG		
ADP1829	2× SW controller	24.0	1.0	3	20.0	—	0.6	EN SS		
ADP1864	SW controller	14.0	3.2	3.2	5.0	—	0.8			•
ADP2102	SW regulator	5.5	2.7		0.6	3.3	0.8	EN		•
ADP2105	SW regulator	5.5	2.7		1.0	5.5	0.8	EN SS		•
ADP2106	SW regulator	5.5	2.7		1.5	5.5	0.8	EN SS		•
ADP2107	SW regulator	5.5	2.7		2.0	5.5	0.8	EN SS		
ADP3050	SW regulator	30.0	3.6		1.5	12	1.25	EN		•
ADP120	LDO	5.5	2.3		0.10	3.3	1.2	EN		•
ADP121	LDO	5.5	2.3		0.15	3.3	1.2	EN		•
ADP130	LDO with bias pin	3.6	1.2	2.3	0.35	3.0	0.8	EN		•
ADP1708	LDO	5.5	2.5		1.00	5.0	0.75	EN SS		•
ADP1710	LDO	5.5	2.5		0.15	5.0	0.75	EN		
ADP1712	LDO	5.5	2.5		0.30	5.0	0.75	EN		•
ADP1715	LDO	5.5	2.5		0.50	5.0	0.75	EN		•
ADP1741 ¹	LDO	3.6	1.6		2.00	3.0	0.8	EN PG SS		•
ADP3339	LDO	6.0	2.8		1.50	5.0	1.5			•
ADP1720	LDO	28.0	4.0		0.05	5.0	1.23	EN		•

¹Indicates UnRel parts. ADI regulators and LDOs are also available in fixed-output voltage options, further reducing external component count.

Operating control features: SS = soft start; EN = enable; PG = power good; TK = tracking; SK = sync.

SW controllers require a separate V_{CC} supply from the power V_{IN} rail.

Refer to ADIsim for a complete set of design tools to create a complete BOM for all of these regulators.

<http://designtools.analog.com/dtPowerWeb/dtPowerMain.aspx>



**Analog Devices, Inc.
Worldwide Headquarters**

Analog Devices, Inc.
One Technology Way
P.O. Box 9106
Norwood, MA 02062-9106
U.S.A.
Tel: 781.329.4700
(800.262.5643,
U.S.A. only)
Fax: 781.461.3113

**Analog Devices, Inc.
Europe Headquarters**

Analog Devices, Inc.
Wilhelm-Wagenfeld-Str. 6
80807 Munich
Germany
Tel: 49.89.76903.0
Fax: 49.89.76903.157

**Analog Devices, Inc.
Japan Headquarters**

Analog Devices, KK
New Pier Takeshiba
South Tower Building
1-16-1 Kaigan, Minato-ku,
Tokyo, 105-6891
Japan
Tel: 813.5402.8200
Fax: 813.5402.1064

**Analog Devices, Inc.
Southeast Asia
Headquarters**

Analog Devices
22/F One Corporate Avenue
222 Hu Bin Road
Shanghai, 200021
China
Tel: 86.21.2320.8000
Fax: 86.21.2320.8222

**Embedded Processing and
DSP Support**

U.S.A.:
processor.support@analog.com
Fax: 781.461.3010
Europe:
processor.europe@analog.com
Fax: 49.89.76903.157
www.analog.com/processors