



VN800S-E VN800PT-E

High-side driver

Datasheet – production data


Features

Type	$R_{DS(on)}$	I_{OUT}	V_{CC}
VN800S-E VN800PT-E	135 m Ω	0.7 A	36 V

- CMOS compatible input
- Thermal shutdown
- Current limitation
- Shorted load protection
- Undervoltage and overvoltage shutdown
- Protection against loss of ground
- Very low stand-by current
- Reverse battery protection
- In compliance with the 2002/95/EC
- European directive

Description

The VN800S-E, VN800PT-E are monolithic devices manufactured using STMicroelectronics® VIPower® M0-3 technology, intended for driving any kind of load with one side connected to ground.



Active V_{CC} pin voltage clamp protects the device against low energy spikes.

Active current limitation combined with thermal shutdown and automatic restart protect the device against overload. Device automatically turns off in case of ground pin disconnection. This device is especially suitable for industrial applications in norms conformity with IEC1131 (Programmable Controllers International Standard).

Table 1. Device summary

Package	Order code	
	Tube	Tape and reel
SO-8	VN800S-E	VN800STR-E
PPAK	VN800PT-E	VN800PTTR-E

Contents

1	Block diagram and pin description	5
2	Electrical specifications	6
2.1	Absolute maximum ratings	6
2.2	Thermal data	7
2.3	Electrical characteristics	8
3	Electrical characteristics curves	14
3.1	Application information	16
3.2	GND protection network against reverse battery	16
3.2.1	Solution 1: resistor in the ground line (RGND only). This can be used with any type of load	16
3.3	Solution 2: a diode (DGND) in the ground line	17
3.3.1	MCU I/Os protection	17
3.4	SO-8 maximum demagnetization energy ($V_{CC} = 13.5\text{ V}$)	18
3.5	PPAK maximum demagnetization energy ($V_{CC} = 13.5\text{ V}$)	19
4	Package and PCB thermal data	20
4.1	SO-8 thermal data	20
4.2	PPAK thermal data	23
5	Package and packing information	26
5.1	ECOPACK®	26
5.2	SO-8 package mechanical data	26
5.3	PPAK package mechanical data	28
6	Revision history	32

List of tables

Table 1.	Device summary	1
Table 2.	Suggested connections for unused and n.c. pins	5
Table 3.	Absolute maximum ratings	6
Table 4.	Thermal data	7
Table 5.	Power	8
Table 6.	Switching (VCC =24 V)	8
Table 7.	Input pin	8
Table 8.	VCC output diode	9
Table 9.	Status pin	9
Table 10.	Protections	9
Table 11.	Truth table	10
Table 12.	Electrical transient requirements on VCC pin (part 1/3)	11
Table 13.	Electrical transient requirements on VCC pin (part 2/3)	11
Table 14.	Electrical transient requirements on VCC pin (part 3/3)	11
Table 15.	Thermal parameter	21
Table 16.	Thermal parameter	25
Table 17.	SO-8 mechanical data	26
Table 18.	PPAK mechanical data	29
Table 19.	Revision history	32

List of figures

Figure 1.	Block diagram	5
Figure 2.	Configuration diagram (top view)	5
Figure 3.	Current and voltage conventions	6
Figure 4.	Status timings	10
Figure 5.	Switching time waveforms	10
Figure 6.	Peak short circuit current test circuit	12
Figure 7.	Avalanche energy test circuit	12
Figure 8.	Waveforms	13
Figure 9.	Off-state output current	14
Figure 10.	High level input current	14
Figure 11.	Status leakage current	14
Figure 12.	On state resistance vs V_{CC}	14
Figure 13.	On-state resistance Vs T_{case}	14
Figure 14.	Input high level	14
Figure 15.	Input low level	15
Figure 16.	Input hysteresis voltage	15
Figure 17.	Turn-on voltage slope	15
Figure 18.	Turn-off voltage slope	15
Figure 19.	Overvoltage shutdown	15
Figure 20.	I_{LIM} vs T_{case}	15
Figure 21.	Application schematic	16
Figure 22.	SO-8 Maximum turn-off current versus load inductance	18
Figure 23.	PPAK maximum turn-off current versus load inductance	19
Figure 24.	SO-8 PC board	20
Figure 25.	SO-8 $R_{thj-amb}$ vs PCB copper area in open box free air condition	20
Figure 26.	SO-8 thermal impedance junction ambient single pulse	21
Figure 27.	Thermal fitting model of a single channel HSD in SO-8	21
Figure 28.	PPAK PC board	23
Figure 29.	PPAK $R_{thj-amb}$ vs PCB copper area in open box free air condition	23
Figure 30.	PPAK thermal impedance junction ambient single pulse	24
Figure 31.	Thermal fitting model of a single channel HSD in PPAK	24
Figure 32.	SO-8 package dimensions	26
Figure 33.	PPAK package dimensions	28
Figure 34.	SO-8 tube shipment (no suffix)	29
Figure 35.	SO-8 tape and reel shipment (suffix "TR")	30
Figure 36.	PPAK suggested pad layout and tube shipment (no suffix)	30
Figure 37.	PPAK tape and reel shipment (suffix "TR")	31

1 Block diagram and pin description

Figure 1. Block diagram




Figure 2. Configuration diagram (top view)





Table 2. Suggested connections for unused and n.c. pins

Connection / Pin	Status	N.C.	Output	Input
Floating	X	X	X	X
To Ground		X		Through 10KΩ resistor

2 Electrical specifications

Figure 3. Current and voltage conventions



2.1 Absolute maximum ratings

Stressing the device above the rating listed in the [Table 4](#) may cause permanent damage to the device. These are stress ratings only and operation of the device at these or any other conditions above those indicated in the operating sections of this specification is not implied. Exposure to Absolute maximum rating conditions for extended periods may affect device reliability. Refer also to the STMicroelectronics sure program and other relevant quality document.

Table 3. Absolute maximum ratings

Symbol	Parameter	Value		Unit
		SO-8	PPAK	
V_{CC}	DC supply voltage	41		V
$-V_{CC}$	Reverse DC supply voltage	- 0.3		V
$-I_{GND}$	DC reverse ground pin current	- 200		mA
I_{OUT}	DC output current	Internally Limited		A
$-I_{OUT}$	Reverse DC output current	- 6		A
I_{IN}	DC input current	+/- 10		mA
V_{IN}	Input voltage range	$-3/+V_{CC}$		V
V_{STAT}	DC Status voltage	$+V_{CC}$		V
V_{ESD}	Electrostatic discharge (human body model: $R=1.5KW$; $C=100pF$)			
	- INPUT	4000		V
	- STATUS	4000		V
	- OUTPUT	5000		V
	- V_{CC}	5000		V

Table 3. Absolute maximum ratings (continued)

Symbol	Parameter	Value		Unit
		SO-8	PPAK	
P_{tot}	Power dissipation $T_C=25^{\circ}\text{C}$	4.2	41.7	W
E_{MAX}	Maximum switching energy ($L=77.5\text{mH}$; $R_L=0\Omega$; $V_{bat}=13.5\text{V}$; $T_{jstart}=150^{\circ}\text{C}$; $I_L=1.5\text{A}$)	121		mJ
E_{MAX}	Maximum switching energy ($L=125\text{mH}$; $R_L=0\Omega$; $V_{bat}=13.5\text{V}$; $T_{jstart}=150^{\circ}\text{C}$; $I_L=1.5\text{A}$)		195	mJ
T_j	Junction operating temperature	Internally limited		$^{\circ}\text{C}$
T_C	Case operating temperature	- 40 to 150		$^{\circ}\text{C}$
T_{stg}	Storage temperature	- 55 to 150		$^{\circ}\text{C}$
L_{max}	Max inductive load ($V_{CC}=30\text{ V}$; $I_{LOAD}=0.5\text{ A}$; $T_{amb}=100^{\circ}\text{C}$; $R_{th_{case>ambient}}\leq 25^{\circ}\text{C/W}$)		2	H

2.2 Thermal data

Table 4. Thermal data

Symbol	Parameter		Value		Unit
			SO-8	PPAK	
$R_{thj-case}$	Thermal resistance junction-case	Max	-	3	$^{\circ}\text{C/W}$
$R_{thj-lead}$	Thermal resistance junction-lead	Max	30	-	$^{\circ}\text{C/W}$
$R_{thj-amb}$	Thermal resistance junction-ambient	Max	93 ⁽¹⁾	78 ⁽²⁾	$^{\circ}\text{C/W}$
		Max	82 ⁽³⁾	45 ⁽⁴⁾	$^{\circ}\text{C/W}$

1. When mounted on FR4 printed circuit board with 0.5 cm² of copper area (at least 35μm thick) connected to all V_{CC} pins
2. When mounted on FR4 printed circuit board with 2 cm² of copper area (at least 35μm thick).
3. When mounted on FR4 printed circuit board with 0.5 cm² of copper area (at least 35μm thick) connected to all V_{CC} pins.
4. When mounted on FR4 printed circuit board with 6 cm² of copper area (at least 35μm thick).

2.3 Electrical characteristics

Values specified in this section are for $8V < V_{CC} < 36V$; $-40^{\circ}C < T_j < 150^{\circ}C$ unless otherwise specified.

Table 5. Power

Symbol	Parameter	Test conditions	Min.	Typ.	Max.	Unit
V_{CC}	Operating supply voltage		5.5		36	V
V_{USD}	Undervoltage shut-down		3	4	5.5	V
V_{OV}	Overvoltage shut-down		36	42		V
R_{ON}	On state resistance	$I_{OUT} = 0.5A$; $T_j = 25^{\circ}C$ $I_{OUT} = 0.5A$			135 270	$m\Omega$ $m\Omega$
I_S	Supply current	Off State; $V_{CC} = 24V$; $T_{case} = 25^{\circ}C$ On State; $V_{CC} = 24V$ On State; $V_{CC} = 24V$; $T_{case} = 100^{\circ}C$		10 1.5	20 3.5 2.6	μA mA mA
I_{LGND}	Output current at turn-off	$V_{CC} = V_{STAT} = V_{IN} = V_{GND} = 24V$; $V_{OUT} = 0V$			1	mA
$I_{L(off1)}$	Off-state output current	$V_{IN} = V_{OUT} = 0V$	0		50	μA
$I_{L(off2)}$	Off-state output current	$V_{IN} = V_{OUT} = 0V$; $V_{CC} = 13V$; $T_j = 125^{\circ}C$			5	μA
$I_{L(off3)}$	Off-state output current	$V_{IN} = V_{OUT} = 0V$; $V_{CC} = 13V$; $T_j = 25^{\circ}C$			3	μA

Table 6. Switching ($V_{CC} = 24V$)

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$t_{d(on)}$	Turn-on delay time	$R_L = 48\Omega$ from V_{IN} rising edge to $V_{OUT} = 2.4V$	-	10	-	μs
$t_{d(off)}$	Turn-off delay time	$R_L = 48\Omega$ from V_{IN} falling edge to $V_{OUT} = 21.6V$	-	40	-	μs
$dV_{OUT}/dt_{(on)}$	Turn-on voltage slope	$R_L = 48\Omega$ from $V_{OUT} = 2.4V$ to $V_{OUT} = 19.2V$	-	See Figure 17	-	V/ μs
$dV_{OUT}/dt_{(off)}$	Turn-off voltage slope	$R_L = 48\Omega$ from $V_{OUT} = 21.6V$ to $V_{OUT} = 2.4V$	-	See Figure 18	-	V/ μs

Table 7. Input pin

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
V_{INL}	Input low level				1.25	V
I_{INL}	Low level input current	$V_{IN} = 1.25V$	1			μA
V_{INH}	Input high level		3.25			V

Table 7. Input pin (continued)

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
I_{INH}	High level input current	$V_{IN}=3.25V$			10	μA
$V_{I(hyst)}$	Input hysteresis voltage		0.5			V
I_{IN}	Input current	$V_{IN}=V_{CC}=36V$			200	μA

Table 8. V_{CC} output diode

Symbol	Parameter	Test conditions	Min.	Typ.	Max.	Unit
V_F	Forward on voltage	$-I_{OUT}=0.6A$; $T_J=150^{\circ}C$	-	-	0.6	V

Table 9. Status pin

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
V_{STAT}	Status Low Output Voltage	$I_{STAT}=1.6\text{ mA}$	-	-	0.5	V
I_{LSTAT}	Status Leakage Current	Normal Operation; $V_{STAT}=V_{CC}=36V$	-	-	10	μA
C_{STAT}	Status Pin Input Capacitance	Normal Operation; $V_{STAT}=5V$	-	-	30	pF

Table 10. Protections⁽¹⁾

Symbol	Parameter	Test conditions	Min	Typ	Max	Unit
T_{TSD}	Shut-down temperature	-	150	175	200	$^{\circ}C$
T_R	Reset temperature	-	135			$^{\circ}C$
T_{hyst}	Thermal hysteresis	-	7	15		$^{\circ}C$
T_{SDL}	Status delay in overload condition	$T_J > T_{jsh}$			20	μs
I_{lim}	DC short circuit current	$V_{CC}=24V$; $R_{LOAD}=10m\Omega$	0.7		2	A
V_{demag}	Turn-off output clamp voltage	$I_{OUT}=0.5\text{ A}$; $L=6mH$	$V_{CC}-47$	$V_{CC}-52$	$V_{CC}-57$	V

1. To ensure long term reliability under heavy overload or short circuit conditions, protection and related diagnostic signals must be used together with a proper software strategy. If the device is subjected to abnormal conditions, this software must limit the duration and number of activation cycles.

Figure 4. Status timings




Figure 5. Switching time waveforms




Table 11. Truth table

Conditions	Input	Output	Status
Normal operation	L	L	H
	H	H	H
Current limitation	L	L	H
	H	X	$(T_j < T_{TSD})$ H $(T_j > T_{TSD})$ L
Overtemperature	L	L	H
	H	L	L
Undervoltage	L	L	X
	H	L	X
Overvoltage	L	L	H
	H	L	H

Table 12. Electrical transient requirements on V_{CC} pin (part 1/3)

ISO T/R 7637/1 Test Pulse	TEST LEVELS				
	I	II	III	IV	Delays and Impedance
1	-25 V	-50 V	-75 V	-100 V	2 ms 10 Ω
2	+25 V	+50 V	+75 V	+100 V	0.2 ms 10 Ω
3a	-25 V	-50 V	-100 V	-150 V	0.1 μ s 50 Ω
3b	+25 V	+50 V	+75 V	+100 V	0.1 μ s 50 Ω
4	-4 V	-5 V	-6 V	-7 V	100 ms, 0.01 Ω
5	+26.5 V	+46.5 V	+66.5 V	+86.5 V	400 ms, 2 Ω

Table 13. Electrical transient requirements on V_{CC} pin (part 2/3)

ISO T/R 7637/1 Test Pulse	TEST LEVELS			
	I	II	III	IV
1	C	C	C	C
2	C	C	C	C
3a	C	C	C	C
3b	C	C	C	C
4	C	C	C	C
5	C	E	E	E

Table 14. Electrical transient requirements on V_{CC} pin (part 3/3)

Class	Contents
C	All functions of the device are performed as designed after exposure to disturbance.
E	One or more functions of the device is not performed as designed after exposure to disturbance and cannot be returned to proper operation without replacing the device.




Figure 6. Peak short circuit current test circuit**Figure 7. Avalanche energy test circuit**

Figure 8. Waveforms



3 Electrical characteristics curves

Figure 9. Off-state output current




Figure 10. High level input current




Figure 11. Status leakage current




Figure 12. On state resistance vs V_{CC}




Figure 13. On-state resistance Vs T_{case}




Figure 14. Input high level




Figure 15. Input low level




Figure 16. Input hysteresis voltage




Figure 17. Turn-on voltage slope




Figure 18. Turn-off voltage slope




Figure 19. Overvoltage shutdown






Figure 20. I_{LIM} vs T_{case}



3.1 Application information

Figure 21. Application schematic



3.2 GND protection network against reverse battery

3.2.1 Solution 1: resistor in the ground line (R_{GND} only). This can be used with any type of load

The following is an indication on how to dimension the R_{GND} resistor.

1. $R_{GND} \leq 600\text{mV} / (I_{S(on)max})$.
2. $R_{GND} \geq (-V_{CC}) / (-I_{GND})$

where $-I_{GND}$ is the DC reverse ground pin current and can be found in the absolute maximum rating section of the device's datasheet.

Power Dissipation in R_{GND} (when $V_{CC} < 0$: during reverse battery situations) is:

$$P_D = (-V_{CC})^2 / R_{GND}$$

This resistor can be shared amongst several different HSD. Please note that the value of this resistor should be calculated with formula (1) where $I_{S(on)max}$ becomes the sum of the maximum on-state currents of the different devices.

Please note that if the microprocessor ground is not common with the device ground then the R_{GND} will produce a shift ($I_{S(on)max} * R_{GND}$) in the input thresholds and the status output values. This shift will vary depending on many devices are ON in the case of several high side drivers sharing the same R_{GND} .

If the calculated power dissipation leads to a large resistor or several devices have to share the same resistor then the ST suggests to utilize [Section 3.3](#).

3.3 Solution 2: a diode (DGND) in the ground line

A resistor ($R_{GND}=1k\Omega$) should be inserted in parallel to D_{GND} if the device will be driving an inductive load.

This small signal diode can be safely shared amongst several different HSD. Also in this case, the presence of the ground network will produce a shift (j600mV) in the input threshold and the status output values if the microprocessor ground is not common with the device ground. This shift will not vary if more than one HSD shares the same diode/resistor network.

Series resistor in INPUT and STATUS lines are also required to prevent that, during battery voltage transient, the current exceeds the Absolute Maximum Rating.

Safest configuration for unused INPUT and STATUS pin is to leave them unconnected.

3.3.1 MCU I/Os protection

If a ground protection network is used and negative transients are present on the V_{CC} line, the control pins are pulled negative. ST suggests to insert a resistor (R_{prot}) in line to prevent the μC I/Os pins to latch-up.

The value of these resistors is a compromise between the leakage current of microcontroller and the current required by the HSD I/Os (Input levels compatibility) with the latch-up limit of microcontroller I/Os.

$$-V_{CCpeak}/I_{latchup} \leq R_{prot} \leq (V_{OH\mu C} - V_{IH} - V_{GND}) / I_{IHmax}$$

Calculation example:


For $V_{CCpeak} = -100V$ and $I_{latchup} \geq 20mA$; $V_{OH\mu C} \geq 4.5V$

$$5k\Omega \leq R_{prot} \leq 65k\Omega.$$

Recommended R_{prot} value is $10k\Omega$.

3.4 SO-8 maximum demagnetization energy ($V_{CC} = 13.5\text{ V}$)


Figure 22. SO-8 Maximum turn-off current versus load inductance



Note: Values are generated with $R_L=0\Omega$. In case of repetitive pulses, T_{jstart} (at beginning of each demagnetization) of every pulse must not exceed the temperature specified above for curves B and C.

3.5 PPAK maximum demagnetization energy ($V_{CC} = 13.5\text{ V}$)

Figure 23. PPAK maximum turn-off current versus load inductance




Note: Values are generated with $R_L=0\Omega$. In case of repetitive pulses, T_{jstart} (at beginning of each demagnetization) of every pulse must not exceed the temperature specified above for curves B and C.

4 Package and PCB thermal data

4.1 SO-8 thermal data

Figure 24. SO-8 PC board



Note: Layout condition of R_{th} and Z_{th} measurements (PCB FR4 area= 58mm x 58mm, PCB thickness=2mm, Cu thickness=35 μ m, Copper areas: 0.14cm², 2cm²).

Figure 25. SO-8 $R_{thj-amb}$ vs PCB copper area in open box free air condition





Figure 26. SO-8 thermal impedance junction ambient single pulse



Equation 1 pulse calculation formula

$$Z_{TH\delta} = R_{TH} \cdot \delta + Z_{THtp}(1 - \delta)$$

where $\delta = t_p/T$

Figure 27. Thermal fitting model of a single channel HSD in SO-8




Table 15. Thermal parameter


Area/island (cm ²)	0.14	2
R1 (°C/W)	0.24	-
R2 (°C/W)	1.2	-
R3 (°C/W)	4.5	-
R4 (°C/W)	21	-

Table 15. Thermal parameter (continued)

Area/island (cm ²)	0.14	2
R5 (°C/W)	16	
R6 (°C/W)	58	28
C1 (W.s/°C)	0.00015	
C2 (W.s/°C)	0.0005	
C3 (W.s/°C)	7.50E-03	
C4 (W.s/°C)	0.045	
C5 (W.s/°C)	0.35	
C6 (W.s/°C)	1.05	2

4.2 PPAK thermal data

Figure 28. PPAK PC board



Note: Layout condition of R_{th} and Z_{th} measurements (PCB FR4 area= 60mm x 60mm, PCB thickness=2mm, Cu thickness=35 μ m, Copper areas: 0.44cm², 8cm²).

Figure 29. PPAK $R_{thj-amb}$ vs PCB copper area in open box free air condition





Figure 30. PPAK thermal impedance junction ambient single pulse



Equation 2 Pulse calculation formula

$$Z_{TH\delta} = R_{TH} \cdot \delta + Z_{THtp}(1 - \delta)$$

where $\delta = t_p / T$

Figure 31. Thermal fitting model of a single channel HSD in PPAK




Table 16. Thermal parameter

Ara/island (cm ²)	0.44	6
R1 (°C/W)	0.04	
R2 (°C/W)	0.25	
R3 (°C/W)	0.3	
R4 (°C/W)	2	
R5 (°C/W)	15	
R6 (°C/W)	61	24
C1 (W.s/°C)	0.0008	
C2 (W.s/°C)	0.007	
C3 (W.s/°C)	0.02	
C4 (W.s/°C)	0.3	
C5 (W.s/°C)	0.45	
C6 (W.s/°C)	0.8	5

5 Package and packing information

5.1 ECOPACK®

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK® packages, depending on their level of environmental compliance. ECOPACK® specifications, grade definitions and product status are available at: www.st.com. ECOPACK® is an ST trademark.

5.2 SO-8 package mechanical data

Figure 32. SO-8 package dimensions




Table 17. SO-8 mechanical data

Symbol	millimeters		
	Min	Typ	Max
A			1.75
a1	0.1		0.25
a2			1.65
a3	0.65		0.85

Table 17. SO-8 mechanical data (continued)

Symbol	millimeters		
	Min	Typ	Max
b	0.35		0.48
b1	0.19		0.25
C	0.25		0.5
c1	45 (typ.)		
D	4.8		5
E	5.8		6.2
e		1.27	
e3		3.81	
F	3.8		4
L	0.4		1.27
M			0.6
S	8 (max.)		
L1	0.8		1.2

5.3 PPAK package mechanical data

Figure 33. PPAK package dimensions




Table 18. PPAK mechanical data

Symbol	millimeters		
	Min	Typ	Max
A	2.20		2.40
A1	0.90		1.10
A2	0.03		0.23
B	0.40		0.60
B2	5.20		5.40
C	0.45		0.60
C2	0.48		0.60
D1		5.1	
D	6.00		6.20
E	6.40		6.60
E1		4.7	
e		1.27	
G	4.90		5.25
G1	2.38		2.70
H	9.35		10.10
L2		0.8	1.00
L4	0.60		1.00
L5	1		
L6		2.80	
R		0.2	
V2	0°		8°
Package Weight	Gr. 0.3		

Figure 34. SO-8 tube shipment (no suffix)




Figure 35. SO-8 tape and reel shipment (suffix “TR”)




Figure 36. PPAK suggested pad layout and tube shipment (no suffix)





Figure 37. PPAK tape and reel shipment (suffix “TR”)



6 Revision history

Table 19. Revision history

Date	Revision	Changes
7-Oct-2004	1	Initial release.
02-May-2012	2	Update entire document following new ST template. Update Figure 33 and Table 18 .
20-Sep-2013	3	Updated Disclaimer.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

ST PRODUCTS ARE NOT DESIGNED OR AUTHORIZED FOR USE IN: (A) SAFETY CRITICAL APPLICATIONS SUCH AS LIFE SUPPORTING, ACTIVE IMPLANTED DEVICES OR SYSTEMS WITH PRODUCT FUNCTIONAL SAFETY REQUIREMENTS; (B) AERONAUTIC APPLICATIONS; (C) AUTOMOTIVE APPLICATIONS OR ENVIRONMENTS, AND/OR (D) AEROSPACE APPLICATIONS OR ENVIRONMENTS. WHERE ST PRODUCTS ARE NOT DESIGNED FOR SUCH USE, THE PURCHASER SHALL USE PRODUCTS AT PURCHASER'S SOLE RISK, EVEN IF ST HAS BEEN INFORMED IN WRITING OF SUCH USAGE, UNLESS A PRODUCT IS EXPRESSLY DESIGNATED BY ST AS BEING INTENDED FOR "AUTOMOTIVE, AUTOMOTIVE SAFETY OR MEDICAL" INDUSTRY DOMAINS ACCORDING TO ST PRODUCT DESIGN SPECIFICATIONS. PRODUCTS FORMALLY ESCC, QML OR JAN QUALIFIED ARE DEEMED SUITABLE FOR USE IN AEROSPACE BY THE CORRESPONDING GOVERNMENTAL AGENCY.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2013 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com