

## FPD87352CXA +3.3V TFT-LCD Timing Controller with Single LVDS Input/Dual RSDS™ Outputs Including RTC (Response Time Compensation) for TFT-LCD Monitors and TV (XGA/WXGA/HDTV I,II,-)

Check for Samples: [FPD87352](#)

### FEATURES

- Input Frequency Range from 30 MHz to 95 MHz
- Support Display Resolutions XGA (1024x768), WXGA (1280x768), HDTV I (1280x768), HDTV II (1366x768) and HDTV - (1280x800)
- Embedded Gate Array for Custom Panel Timing
- LVDS Single Pixel Input (8-Bit/6-Bit) Interface (FPD-Link)
- RSDS Dual Bus Output (8-Bit/6-Bit)
- Drives RSDS Column Drivers up to 47.5 MHz Clock
- Flexible RSDS Data Output Mapping for Bottom or Top Mount
- RTC (Response Time Compensation) Function
- 2 Wired Serial EEPROM Interface Support (RTC LUT)
- Interface with External Frame Memory
- Virtual 8-Bit Color Depth in FRC/Dithering Mode
- Supports Graphics Controllers with Spread Spectrum Interface for Lower EMI
- Supports External Spread Spectrum (SSCG)
- DE Only Mode
- CMOS Circuitry Operates from 3.0V–3.6V; 0°C–70°C
- 176 LQFP Package with Body Size 24 mm x 24 mm x 1.4 mm, 0.5 mm Pitch

### DESCRIPTION

The FPD87352CXA is an integrated FPD-Link™ + RSDS + TFT-LCD Timing Controller. The logic architecture is implemented using standard and default timing controller functionality based on an Embedded Gate Array. The device is reconfigurable to the needs of a specific application by providing user-defined specifications or customer supplied VHDL/Verilog code.

The FPD87352CXA is an ideal Timing Controller for LCD TV Applications. It has a unique feature, RTC that will improve the intra-gray level response time of a LCD TV panel. Improving the intra-gray level response time of the LCD panel will result in a dramatically improved Motion Picture Image Quality of video content that are displayed on the LCD panel. The RTC feature is accomplished through application of a Boost or Overdrive Voltage that will force the LC material to respond more rapidly. This Boost or Overdrive is accomplished through combination of an internal or external EEPROM LUT (Look Up Table), which contains the boost/overdrive levels, and external memory that acts as a Frame Buffer.

The FPD87352CXA is a timing controller that combines an LVDS single pixel input interface with National's Reduced Swing Differential Signaling (RSDS) output column driver interface for XGA/WXGA/HDTV I,II,- resolutions. It resides on the Flat Panel Display and provides the data buffering and control signal generation. FPD-Link, a lower dynamic power, low EMI (Electro Magnetic Interference) interface is used between this timing controller and the host system. A RSDS interface is used between the timing controller and the column drivers.

The dual 13/10 pair differential bus conveys up to 24-bit color data for XGA, WXGA and HDTV panels.



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

RSDS is a trademark of Texas Instruments.

All other trademarks are the property of their respective owners.

## System Diagram




Figure 1. Block Diagram of the LCD Module

## Block Diagram




Figure 2. Block Diagram

## Function Description

### FPD-LINK RECEIVER

The LVDS based FPD-Link Receiver receives input video data and control timing. Four LVDS channels plus clock provide 24-bit color.

RESETN initializes the chip with the default register values for the LUT values from internal ROM or external EEPROM.

### SSC (SPREAD SPECTRUM CONTROL)

This SSC function provides a means for reducing EMI. This feature uses external SSC signal source that provides synchronized spread spectrum for RSFS and control signal outputs.

### 2-WIRE SERIAL EEPROM INTERFACE

The Serial EEPROM Interface controls the FPD87352CXA initialization of LUT register. If the EEPROM is not present, the LUT value is provided by internal ROM of FPD87352CXA.

### CLK & DATA SYNCHRONIZER

This function delays and aligns data to match the internal data process which included RSFS skew control by RSKEW[2:0]. All the data processes are needed to be aligned each data path through RSFS output and LCD timing control signal.

## ***LUT REGISTER***

This block provides the RTC reference values to be processed on the RTC Data Processor Block. The setting of RTC reference values is provided by the external EEPROM in normal condition. If the external EEPROM is not present it will use the internal ROM's RTC reference values. The RTC reference values are the new gray values depending on the difference between the current frames' RGB gray data and the previous frame's RGB gray data of same pixel.

## ***RTC DATA PROCESSOR***

This function generates new gray values depending on the difference of the current RGB gray data and same pixel of the previous frame. The reference values fetch from the LUT (Look Up Table) values in the LUT Register.

## ***RSDS INTERFACE WITH SKEW CONTROL***

This functional block transforms CMOS level signal to RSDS for the system clock (DCLK) and RGB color data. The RSDS skew is controlled by RSKEW[2:0] with delay steps between the RSF/BCKP/N and RSF/BR/G/B[3:0]P/N which is implemented in CLK & Data synchronizer.

## ***VERTICAL & HORIZONTAL LCD TIMING CONTROL***

This function block generates the TTL(CMOS) level signal for the interface of column drivers and row drivers in the LCD system. All signals are synchronized by RSF/BCKP/N which is RSDS data clock for the column drivers. The clock skew control must not change the typical timing of TTL(CMOS) level signals.

## REVISION HISTORY

| Changes from Revision B (April 2013) to Revision C         | Page              |
|------------------------------------------------------------|-------------------|
| • Changed layout of National Data Sheet to TI format ..... | <a href="#">4</a> |

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

|                              |                                                                                      |
|------------------------------|--------------------------------------------------------------------------------------|
| Audio                        | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers                   | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters              | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products                | <a href="http://www.dlp.com">www.dlp.com</a>                                         |
| DSP                          | <a href="http://dsp.ti.com">dsp.ti.com</a>                                           |
| Clocks and Timers            | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface                    | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                        | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt                   | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers             | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                         | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Applications Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity        | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |                                                                                          |
|-------------------------------|------------------------------------------------------------------------------------------|
| Automotive and Transportation | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)