

Power management (dual transistors)

UMF28N

2SA1774 and DTC124XE are housed independently in a UMT package.

●Application

Power management circuit


●Features

- 1) Power switching circuit in a single package.
- 2) Mounting cost and area can be cut in half.


●Structure

Silicon epitaxial planar transistor

●Equivalent circuit



●External dimensions (Unit : mm)



●Packaging specifications

Type	UMF28N
Package	UMT6
Marking	F28
Code	TR
Basic ordering unit (pieces)	3000

Transistors

●Absolute maximum ratings (Ta=25°C)

Tr1

Parameter	Symbol	Limits	Unit
Collector-base voltage	V _{CBO}	−60	V
Collector-emitter voltage	V _{CEO}	−50	V
Emitter-base voltage	V _{EBO}	−6	V
Collector current	I _C	−150	mA
Collector power dissipation	P _C	150 (TOTAL)	mW *
Junction temperature	T _j	150	°C
Storage temperature	T _{stg}	−55 to +150	°C

* 120mW per element must not be exceeded.

DTr2

Parameter	Symbol	Limits	Unit
Supply voltage	V _{CC}	50	V
Input voltage	V _{IN}	−10 to +40	V
Output current	I _O	100	mA
	I _{C(Max.)}	100	
Power dissipation	P _C	150(TOTAL)	mW *
Junction temperature	T _j	150	°C
Range of storage temperature	T _{stg}	−55 to +150	°C

* 120mW per element must not be exceeded.
Each terminal mounted on a recommended land.

●Electrical characteristics (Ta=25°C)

Tr1

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV _{CBO}	−60	−	−	V	I _C = −50μA
Collector-emitter breakdown voltage	BV _{CEO}	−50	−	−	V	I _C = −1mA
Emitter-base breakdown voltage	BV _{EBO}	−6	−	−	V	I _E = −50μA
Collector cutoff current	I _{CBO}	−	−	−0.1	μA	V _{CB} = −60V
Emitter cutoff current	I _{EBO}	−	−	−0.1	μA	V _{EB} = −6V
Collector-emitter saturation voltage	V _{CE(sat)}	−	−	−0.5	V	I _C /I _B = −50mA/−5mA
DC current transfer ratio	h _{FE}	180	−	390	−	V _{CE} = −6V, I _C = −1mA
Transition frequency	f _T	−	140	−	MHz	V _{CE} = −12V, I _E = 2mA, f = 100MHz
Output capacitance	C _{ob}	−	4	5	pF	V _{CB} = −12V, I _E = 0A, f = 1MHz

DTr2

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Input voltage	V _{I(off)}	−	−	0.4	V	V _{CC} =5V, I _O =100μA
	V _{I(on)}	2.5	−	−		V _O =0.3V, I _O =2mA
Output voltage	V _{O(on)}	−	0.1	0.3	V	I _O =10mA, I _I =0.5mA
Input current	I _I	−	−	0.36	mA	V _I =5V
Output current	I _{O(off)}	−	−	0.5	μA	V _{CC} =50V, V _I =0V
DC current gain	G _I	68	−	−	−	V _O =5V, I _O =5mA
Input resistance	R ₁	15.4	22	28.6	kΩ	−
Resistance ratio	R ₂ /R ₁	1.7	2.1	2.6	−	−
Transition frequency	f _T	−	250	−	MHz	V _{CE} =10V, I _E = −5mA, f=100MHz *

* Transition frequency of the device.

Transistors

●Electrical characteristics curves

Tr1




Fig.1 Grounded emitter propagation characteristics




Fig.2 Grounded emitter output characteristics (I)




Fig.3 Grounded emitter output characteristics (II)




Fig.4 DC current gain vs. collector current (I)




Fig.5 DC current gain vs. collector current (II)




Fig.6 Collector-emitter saturation voltage vs. collector current (I)




Fig.7 Collector-emitter saturation voltage vs. collector current (II)





Fig.8 Gain bandwidth product vs. emitter current

Fig.9 Collector output capacitance vs. collector-base voltage
Emitter input capacitance vs. emitter-base voltage

Transistors

DTr2




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.