

Configuration:

DB25M	CN36M
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10	10
11	11
12	12
13	13
14	14
15	32
16	31
17	36
18	33
19	19
20	21
21	23
22	25
23	27
24	29
25	30
Shield	Shield

**Notes:**


- 1.Cable: #28, 25C+1+AL/MY,O.D:6.5
- 2.Connector:DB25M, Blue  
CN36M, Blue
- 3.Screw:#4-40UNC
- 4.Snap Hood:DB25, Beige  
CN36, Beige

**Note:**

- 1.Total Length: **SEE "ITEM NO"**
- 2.Color:Beige
- 3.Assembly Type



<i>ITEM NO</i>	<b>AK101-1.8-R (1.8 Meters)</b> <b>AK102-3-R (3 Meters)</b> <b>AK103-5-R (5 Meters)</b> <b>AK104-7M-R (7 Meters)</b> <b>AK105-10M-R (10 Meters)</b>
<i>TITLE</i>	<b>PRINTER CABLE, D-SUB 25 MALE to CENT 36 MALE</b>



1840 W. Drake Drive, Suite 101 - Tempe, AZ 85283  
Toll Free: 1-877-277-6266 Email: info@usa-assmann.com

THIS DRAWING IS UNPUBLISHED  
© Copyright 2008 by Assmann Electronic Components  
All International Rights Reserved